



## SU12000RT4U Estimated Runtime

### Load in Watts

UPS	Battery Pack	BP Qty.	3000W	4000W	4200W	5000W	5500W	6000W	6500W	7000W	7500W	8000W	8400W
SU12000RT4U	Included Batteries	0	28	21	20	15	13	12	10	9	8	8	7
SU12000RT4U	BP192V18-4U	1	88	63	60	48	43	39	35	32	29	27	25
SU12000RT4U	BP192V18-4U	2	144	104	99	80	72	64	58	53	49	45	42
SU12000RT4U	BP192V18-4U	3	202	147	139	114	102	92	83	76	70	64	61
SU12000RT4U	BP192V18-4U	4	261	191	181	149	134	121	109	100	92	85	80
SU12000RT4U	BP192V18-4U	5	320	236	224	185	166	150	136	125	115	106	100
SU12000RT4U	BP192V18-4U	6	380	281	267	221	198	180	163	150	138	128	121
SU12000RT4U	BP192V18-4U	7	440	327	310	257	231	210	191	175	162	150	141
SU12000RT4U	BP192V18-4U	8	500	372	353	294	265	240	219	201	186	172	162
SU12000RT4U	BP192V18-4U	9	559	418	397	330	298	271	247	227	210	195	184
SU12000RT4U	BP192V18-4U	10	619	463	441	367	332	301	275	253	234	217	205
SU12000RT4U	BP192V557C-16K	1	175	126	119	97	86	78	70	64	58	54	50
SU12000RT4U	BP192V557C-16K	2	355	260	247	203	182	165	150	137	126	116	110
SU12000RT4U	BP192V787C-16K	1	282	206	195	160	143	129	117	107	98	90	85
SU12000RT4U	BP192V787C-16K	2	574	427	406	337	304	275	251	231	213	197	186
SU12000RT4U	BP192V1037C-16K	1	332	243	230	189	170	153	139	127	117	108	102
SU12000RT4U	BP192V1037C-16K	2	673	503	478	398	360	326	298	274	253	235	222
SU12000RT4U	BP192V1407C-16K	1	454	336	319	264	237	215	195	179	165	153	144
SU12000RT4U	BP192V1407C-16K	2	916	690	657	550	498	453	415	382	354	329	312
SU12000RT4U	BP192V1407C-16K	3	1366	1039	991	834	758	693	636	588	546	509	483
SU12000RT4U	BP192V1407C-16K	4	1801	1380	1318	1114	1015	930	856	792	737	689	654

All runtime values are in minutes.