



## SU40K Estimated Runtime

Load in Watts

UPS	Battery Pack	4000W	8000W	12000W	16000W	18000W	20000W	22000W	24000W	26000W	28000W	30000W	32000W
SU40K	Included Batteries	72	31	19	13	11	10	9	8	7	7	6	5.5
SU40K	+ 1 BP480V26B	184	82	50	34	30	27	24	21	19	18	16	15
SU40K	+1 BP480V40C	258	118	72	50	44	39	35	32	29	26	24	22
SU40K	+1 BP480V55	341	158	98	69	60	54	48	44	40	37	34	31
SU40K	+1 BP480V78	469	223	140	99	87	78	70	64	58	53	49	46
SU40K	+1 BP480V103	609	295	187	133	118	106	95	87	79	73	68	63
SU40K	+1 BP480V140	815	402	258	186	165	149	134	123	112	104	96	89
SU40K	+2 BP480V78	903	449	290	209	186	167	152	138	127	117	109	101
SU40K	+2 BP480V103	1176	595	388	283	253	228	207	189	174	161	149	139
SU40K	+2 BP480V140	1571	810	535	394	352	318	290	266	245	227	211	197
SU40K	+3 BP480V103	1722	894	592	437	392	354	323	296	273	253	236	220
SU40K	+3 BP480V140	2286	1209	810	603	542	492	449	413	382	355	331	310
SU40K	+4 BP480V140	2963	1598	1081	811	731	665	609	561	520	484	452	424

All runtime values are in minutes.