



## SMART5000RT3U Estimated Runtime

### Load in Watts

UPS	Battery Pack	500W	1,000W	1,500W	2,000W	2,200W	2,400W	2,600W	2,800W	3,000W	3,500W	3,750W	4,000W
SMART5000RT3U	Included Battery Pack	194	90	56	38	35	31	28	25	23	19	17	15
SMART5000RT3U	1 BP48V60RT3U	366	176	111	79	70	63	57	52	47	39	35	33
SMART5000RT3U	2 BP48V60RT3U	568	281	180	130	115	104	94	86	78	65	59	55
SMART5000RT3U	3 BP48V60RT3U	768	387	251	182	162	146	133	121	111	92	85	78
SMART5000RT3U	4 BP48V60RT3U	967	493	322	235	211	190	173	158	146	121	111	103
SMART5000RT3U	5 BP48V60RT3U	1,163	599	395	289	259	234	213	196	180	150	138	128
SMART5000RT3U	6 BP48V60RT3U	1,356	705	467	344	309	279	255	234	216	180	166	154
SMART5000RT3U	7 BP48V60RT3U	1,547	810	539	398	358	324	296	272	251	210	194	180
SMART5000RT3U	8 BP48V60RT3U	1,734	915	611	453	408	370	338	311	287	241	222	206
SMART5000RT3U	9 BP48V60RT3U	1,920	1,019	683	508	457	415	380	349	323	271	250	232
SMART5000RT3U	10 BP48V60RT3U	2,102	1,122	754	562	507	460	421	388	359	302	279	259

All runtime values are in minutes.